



THE COMMUNICATOR

MONTHLY

Radionics Inc., 1800 Abbott Street, Salinas, CA 93901 • Phone: (408)757-8877 • Fax: (408)757-6093 • www.radionicsinc.com

HIGH RISE APPLICATIONS APPROVED BY CALIFORNIA STATE FIRE MARSHAL

Good News for California Dealers

The California State Fire Marshal (CSFM) has approved Radionics' Fire Alarm Control Panels (FACPs) for use in high-rise applications. The following models have been approved for use in high-rise applications when used with Applied American Technologies, Inc. EVAC 2101-M Emergency Voice Evacuation, Relocation, and Paging System:

- | | | |
|----------|-----------|---------|
| • D10024 | • D8124 | • D9124 |
| • D7212 | • D7212B1 | • D7412 |
| • D9112 | • D9112B1 | • D9412 |

This high-rise application approval by the CSFM is a first for Radionics and allows the products listed above to meet the high-rise requirements in California which differ from most states.

Customers may purchase the required voice evacuation system directly from Radionics by ordering a 2101-RMT. Other evacuation accessories are also available, refer to the Radionics Fire Products Catalog, L741 for additional information.



RADXONCD NEWS

The RADXonCD's Beta version 1.0 was well received by many of you. However, there were a few minor problems that some of you brought to our attention, and we are currently fixing for a final version release this November.

For those of you who have the first Beta release version, here is a helpful hint. If you are experiencing a "General Protection Fault" message from Windows 95, we recommended

doing the following: before going into Acrobat to view the documents, shut off the Video by clicking on the "toggle switch" that says "OFF" in the lower right hand corner of the screen. This will stop the video from playing and allow you to enter into the documents. If this does not help, use windows Explorer, and click on your cdrom drive, and look for the file name documents.pdf. Double click this file and the document

menu will come up launching only Acrobat. This will eliminate any conflict between The Video and acrobat. (This message occurs because the Video on the first menu screen is still running behind the Acrobat documents menu).

If you have any further comments on the RADXonCD please call the Marketing Communications Dept. at 1-800-538-5807 ext. 1210.



NEW RADIONICS CONTROL / COMMUNICATOR PRODUCT COMPARISON CHART

The chart below list the most recent comparison table of the Radionics panels and their available features. Your sales personnel and installers may use this chart to specify, or compare features of the Radionics panels.

FEATURES	D2012U	D2112	D2212	D2412U	D7212	D7412	D9112	D9412
Zones / Points	6	8	8-24	6-24	8-75	8-75	8-246	8-246
Areas of Protection	1	1	1	1	8	8	8	8
Passcode Users	8	8	8	8	100*	100*	250*	250*
Passcode User Windows	NONE	NONE	NONE	NONE	8	8	8	8
Access Control Doors	NONE	NONE	NONE	NONE	NONE	2	NONE	8
Access Cards / Keys	NONE	NONE	NONE	NONE	NONE	396	NONE	996
Authority Levels	3	3	3	3	15*	15*	15*	15*
Command Centers	8	4	8	8	32	32	32	32
Alpha Display	YES	NO	YES	YES	YES	YES	YES	YES
Function Keys	3	3	3	3	3 (D720)	3 (D720)	3 (D720)	3 (D720)
Custom Function Menus	N/A	N/A	N/A	N/A	4	4	16	16
Event Logger	NONE	NONE	NONE	NONE	Up to 1000			
Local Printer (s)	NONE	NONE	NONE	NONE	1	1	3	3
Auxiliary Power Available	500 mA	350 mA	1 amp	1 amp	1.4 amps	1.4 amps	1.4 amps	1.4 amps
Number of Aux. Outputs	2	2	2	2	1	1	1	1
Alarm Power Available	1.5 amps	1.5 amps	1.85 amps	1.85 amps	2 amps	2 amps	2 amps	2 amps
Number of Alarm Outputs	1	1	1	1	2	2	2	2
Relay Dry Contacts					64	64	128	128
Auto Resetting Power Protection	YES	YES	YES	YES	YES	YES	YES	YES
UL Burglary	C & R	C & R	C & R	C & R	C & R	C & R	C & R	C & R
UL Fire	R	R	R	R	C & R	C & R	C & R	C & R
UL Access Control	N/A	N/A	N/A	N/A	N/A	YES	N/A	YES
Department of Defense	NO	NO	NO	NO	YES	YES	YES	YES
Phone Line(s) Monitor	NO	NO	NO	NO	YES	YES	YES	YES
UPLINK model 1500 compatible	YES	YES	YES	YES	YES	YES	YES	YES
UPLINK model 1600 compatible	YES	NO	NO	YES	NO	NO	NO	NO
Automatic Test Report	YES	YES	YES	YES	YES	YES	YES	YES
Remote Programmable	YES	YES	YES	YES	YES	YES	YES	YES
Fully keypad Programmable	YES	YES	YES	YES	NO	NO	NO	NO
Scheduled Events	NONE	NONE	NONE	NONE	40	40	40	40
Wireless Compatible Databus	NO	NO	YES	YES	NO	NO	NO	NO
Sub-zone Control	YES	YES	YES	YES	YES	YES	YES	YES
Keyswitch Control	YES	YES	YES	YES	YES	YES	YES	YES

* Includes Service Passcode

C = Commercial
R = Residential

N/A = Not Applicable



Radionics' 1997 National Training Schedule

DATE	SEMINAR	CONTENT	DAY	LOCATION	TRAINER
NOVEMBER 1997					
11/11/97	Readykey (A)	Readykey	4	Chicago, IL (Actual location pending)	M. Dreksler
DECEMBER 1997					
12/15/97	Readykey (A)	Readykey	4	San Diego, CA (Actual location pending)	M. Dreksler

Seminar registration forms are published five to six weeks prior to the seminar date and can be obtained by calling the National Training Dept. at (800) 538-5807 ext. 1258.

Radionics Inc. reserves the right to cancel any seminar that does not meet the minimum requirement of at least 7 attendees within 14 days of the scheduled seminar date.


1997 Price Code:

A = \$250.00 Per Person

Regional seminars are no charge to all Radionics dealers



ENJOY THE THANKSGIVING



All of us at Radionics, would like to wish all of you a Happy and Healthy Thanksgiving Holiday, this November.

We also would like to announce that on November 27th and 28th, (Thanksgiving Holiday),

Radionics will be closed. That includes the following departments: Order Processing, Tech Support and Shipping. Radionics will resume business on Monday, December 1st.

Until then we hope you all have a very enjoyable Thanksgiving holiday with your family.



Tech Tips

Frequently Asked Questions

Q: When Updating the D6500 from MPU rev 7.80, what needs to be ordered?

A: If you previously had MPU rev 7.10, 7.76, or higher, order one D6590M-0800 for each of your MPU cards. Your printer and line card revisions are compatible with the new software. If you had any other revision of MPU cards, order one D6590M-0800 for each MPU card, one D6590P-0303 for each printer, and one #26-04659-0700 for each line card.

Frank Foley

Technical Support Representative

Q: How can the strobes be configured so that they continue to flash yet have the horns silenced by the passcode in the 7000/9000 series panels?

A: It will require two Notification Appliance Circuits (NACs). Use two Bell Supervision Modules (D192C/D) and a D411 (for 2-wire horn/strobes) or the D412 (for older models with separate audible/strobe inputs). The first D192 will be used for the audible circuit triggered by the Fire Bell Relay and connected to the D411 (D412) Audible Ckt input, terminated with a 560 ohm EOL. The second D192 is for the strobes triggered by the Summary Fire Relay and connected to the D411 (D412) Strobe Ckt input, terminated with a 560 ohm EOL (end-of-line), or at the NAC circuit.

Eric Spansel

Technical Support Representative

Q: What are the new, flat, direct print style cards for the Readykey system?

A: You have three options when ordering these new cards. (1) The K2011B-10 is a package of 10 cards. These have the Radionics logo on one side of the card. (2) The K2011M-10 is a package of 10 cards. They are white on both sides with a non-encoded magnetic stripe on one side of the card. (3) The K2011W-10 is a package of 10 cards. These cards are white on both sides of the card.

NOTE: The K2011A-10 (pkg of 10) cards are also flat cards with the Radionics logo on one side of the card, however they are not suitable for direct printing.

Angela Parks

Readykey Support Representative

BULK RATE
U.S. POSTAGE
PAID
KP Corporation
94578

Access • Fire • Intrusion • Wireless Communications
1800 Abbott Street • Salinas, CA 93901

Radionics

